

BP-2000 JUMPER SETTING

- **JP1 : CMOS DATA CONTROL**
 - Pin 1-2 Short: Normal
 - Pin 2-3 Short : clear CMOS
- **JP2 : COM1/COM2 12V DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 Pin1 connected to 12V
 - Pin 3-5 Short : COM1 Pin1 connected to DCD
 - Pin 2-4 Short : COM2 Pin1 connected to 12V
 - Pin 4-6 Short : COM2 Pin1 connected to DCD
- **JP3 : COM1/COM2 5V DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 Pin9 connected to 5V DC (By BIOS setting)
 - Pin 3-5 Short : COM1 Pin9 connected as RI
 - Pin 2-4 Short : COM2 Pin9 connected to 5V DC (By BIOS setting)
 - Pin 4-6 Short : COM2 Pin9 connected as RI
- **JP5 : COM3/COM4 5V DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 Pin9 connected to 5V DC (By BIOS setting)
 - Pin 3-5 Short : COM1 Pin9 connected as RI
 - Pin 2-4 Short : COM2 Pin9 connected to 5V DC (By BIOS setting)
 - Pin 4-6 Short : COM2 Pin9 connected as RI
- **JP6 : VGA 12V DC SUPPLY SELECT FOR CRT**
 - Open : no 12V Supply to CRT port
 - Short : 12V Output supply to CRT port
- **JP7 : COM3/COM4 12V DC SUPPLY SELECT**
 - Pin 1-3 Short : COM3 Pin1 connected to 12V
 - Pin 3-5 Short : COM3 Pin1 connected to DCD
 - Pin 2-4 Short : COM4 Pin1 connected to 12V
 - Pin 4-6 Short : COM4 Pin1 connected to DCD

